

# COMEGA® QP 2001

COMMAND LIST			
Key	Function	Syntax	Comments
<b>A</b>	Audio	-	Displays Audio Status : Stereo / Mono / Left / Right
		=[S / M / L / R]	Selects audio output: Stereo (S), Mono (M), Left (L), Right (R)
<b>AL</b>	Audio Level	-	Displays Current Audio Level
		=<AudioLevel>	Selects Audio Level: <AudioLevel> between 0 and 20 0=Mute, 1=48dB, 20=0dB
<b>C</b>	Smartcard info.	-	Displays Smartcard Status (This command gives access to a special menu)
<b>I</b>	Information	-	Displays Setup Information
<b>L</b>	LNB	-	Displays LNB Status: OL Low, OL High, LNB Power
		=<OL Low>;<OL High>;[P/N]	Setups LNB Configuration: OL Low, OL High, [Power On (P) / Off (N)]
<b>R</b>	Reboot	-	Performs a Reboot of the QP 2001
<b>S</b>	Service	-	Displays List of Services
		=<M_num>;<S_num> [;<A_num>]	Setups a Service to a Module Module N°, Service N°, [Audio channel N°]
<b>T</b>	Tune	-	Displays Front End
		=<Freq>;<Polar>;<SR>	Setups FrontEnd Values: Frequency in MHz, Polarity ('V'/'H'), Symbol Rate MS/s
<b>TXT</b>	Teletext Output	=[0/1]	Displays Teletext output status: On/Off Setups Teletext output: Enable (1) / Disable (0)
<b>VF</b>	Video Format	=[0/1/2/3]	Changes the Video Format: 0: Disables the Automatic video format signalling 1: Enables the Automatic video format signalling 2: Forces receiver to send WSS signal for 4/3 Video Format 3: Forces receiver to send WSS signal for 16/9e Video Format
<b>W</b>	Watchdog	-	Displays Watchdog Status
		=[0/1/2]	Setups Watchdog Status: Off (0) / On (1) / On without Audio and Video check (2)
<b>XV</b>	Video Mode	=[0/1/2/3]	Activates Video DAC CVBS Only (0), Y/C Only (1), CVBS and RGB (2), All (3)